MICROPOWER GROUP™
POWERFUL SOLUTIONS PARTNER

TECHNICAL DATA

ACCESS 200 36V/340A BATTERY CHARGERS

STATED DATA ACCORDING TO MICROPOWER STANDARD

Family	Access 200
DC Rating	36V/340A
Part number	AU3803
Model code	1AA8501
Part status	Released

SUPPLY

Mains Phase	3
Input Voltage [V]	208-240
Nominal Voltage [V]	208
Rated frequency [Hz]	50-60
Max Mains Current (at nominal mains V) [A]	48
Current at min rated voltage [A]	48
Current at max rated voltage [A]	41,6
Recommended supply fuse class	C
Recommended RCCB class	B
Mains Cable Area [mm2]	4x10 mm2
Mains Cable Length [m]	□2.5
Mains Connector	CEE63
Standby Power Consumption [W]	<15
Power Consumption [W]	16395
Apparent Power Consumption [VA]	17258
Power Factor	0,95
Leakage current [mA]	<3,5
Efficiency (at rated power and no cables) [%]	91

OUTPUT DATA

Reversed polarity protection	Fuse
Short Circuit Protection	Yes
Output Voltage [V]	36
Output Current [A]	340
Battery Cable [mm2]	4/0 AWG
Battery Cable Length [m]	3
Battery Cable Connection (in charger)	M10
Battery Connector (not included)	DIN640
Output fuse, rating [A/VDC]	2x200A/150VDC
Output fuse type	Fast Semiconductor fuse

PROPERTIES

IP Protection	IP20
Operation Temperature [deg C]	-5 to +40
Ambient Max Temperature (with reduced capacity) [deg C]	50
Ambient storage and transport temperature [C]	-40 to +80/1000h
Maximum operating altitude [m]	2000
Maximum humidity, non-condensing [%rh]	90
Cooling	Fan
Cabinet Type	A22
Certifications	CE
Cloud connection	Yes
User interface	LED/Display
Charging Curve Set	Multiple Lead
I/O-cards	Optional
Bluetooth/ NFC connectivity	Yes
Remote connectivity & advanced software functions	Yes

CHARGER DIMENSIONS

Charger Weight excl. Cables [kg]	34
Charger dimensions [mm]	659x256x459

SHIPPING DIMENSIONS

Box dimensions [mm]	435x370x690
Shipping Weight [kg]	46

The information in this document is subject to change without notice and should not be construed as a commitment by Micropower Sweden AB.

Micropower Group
Gullhallavägen 20
SE-352 50 Växjö
Sweden

Phone: +46 (0) 470-72 74 00
sales@micropower.se
www.micropower-group.se