MICROPOWER GROUP™
POWERFUL SOLUTIONS PARTNER

TECHNICAL DATA

MICROPOWER ST100 PB 24V/300A UL BATTERY CHARGERS

STATED DATA ACCORDING TO MICROPOWER STANDARD

Family	ST100
DC Rating	24V/300A
Part number	AV2766-B3
Model code	1AA80N2
Part status	Released

SUPPLY

Mains Phase	3
Input Voltage [V]	480
Nominal Voltage [V]	480
Rated frequency [Hz]	50-60
Max Mains Current (at nominal mains V) [A]	12.0
Current at min rated voltage [A]	-
Current at max rated voltage [A]	-
Recommended supply fuse class	C
Recommended RCCB class	B
Mains Cable Area [mm2]	4xAWG14
Mains Cable Length [m]	⌧2.5
Mains Connector	L16-20P
Standby Power Consumption [W]	<5
Power Consumption [W]	9458
Apparent Power Consumption [VA]	9956
Power Factor	0.95
Leakage current [mA]	<3.5
Efficiency (at rated power and no cables) [%]	93

OUTPUT DATA

Reversed polarity protection	Fuse
Short Circuit Protection	Yes
Output Voltage [V]	24
Output Current [A]	300
Battery Cable [mm2]	4/0 AWG
Battery Cable Length [m]	3
Battery Cable Connection (in charger)	M8
Battery Connector (not included)	DIN320
Output fuse, rating [A/VDC]	400A/150VDC
Output fuse type	Fast Semiconductor fuse

PROPERTIES

IP Protection	IP20
Operation Temperature [deg C]	-5 to +40
Ambient Max Temperature (with reduced capacity) [deg C]	50
Ambient storage and transport temperature [C]	-40 to +80/1000h
Maximum operating altitude [m]	2000
Maximum humidity, non-condensing [%rh]	90
Cooling	Fan
Cabinet Type	A19
Certifications	UL
Cloud connection	Yes
User interface	LED/Display
Charging Curve Set	Multiple Lead
I/O-cards	Optional
Bluetooth/ NFC connectivity	Yes
Remote connectivity & advanced software functions	Yes

CHARGER DIMENSIONS

Charger Weight excl. Cables [kg]	18
Charger dimensions [mm]	571x270x258

SHIPPING DIMENSIONS

Box dimensions [mm]	425x380x690
Shipping Weight [kg]	29

The information in this document is subject to change without notice and should not be construed as a commitment by Micropower Sweden AB.

Micropower Group
Gullhallavägen 20
SE-352 50 Växjö
Sweden

Phone: +46 (0) 470-72 74 00
sales@micropower.se
www.micropower-group.se